

JLC Vertex Detector R&D

Status & Plan

2001 Apr.27
Y. Sugimoto

R&D Items

Spatial Resolution

Beam Test
Laser Test

Radiation Hardness

^{90}Sr (electron) Irradiation
 ^{252}Cf Irradiation
HE electron Irradiation

Detector Thickness

Cooling System
Thermal Deformation

Readout Electronics

Fast Readout (>20MHz)
Compact PCI FADC for DAQ

測定概要(1)

YAG laser

spot size 2x2um

pulse width 10n以下

Prober

走査1um(xy方向)

Temperature 0°C

CCD

読み出し 250kpixels/s(HPK,EEV)

蓄積 2秒(読み出し時間含む)

フレーム数 100フレーム(各照射点)

gain 72.5uV/e-(HPK) 34.6uV/e-(EEV)

吸収長 3um(532nm)1mm(1064nm)

EEV 02-06

3-phase

22x22um

HPK S5466

2-phase

24x24um




YAG laser Prober System

波長変換
 $\lambda=532$ nm
or 1064 nm

モニタカメラ

NDフィルタ
 $10^{-8} \sim 10^{-9}$

モニタカメラ




結果電荷分配 H-Scan (EEV)


Normalized
by Cluster

$$\text{Signal Ratio} = \text{Pixel/Cluster} = P_i / (P_i + P_j)$$

(Gateによる影響を
除き、電荷分配のみ
を取り出す。)



532nm




1064nm

V-Scan (EEV)




Normalized
by Cluster



532nm


▲ 72
■ 73
▲ 74




1064nm

◆ 72
■ 73
▲ 74


H-Scan (HPK)



Normalized
by Cluster




532nm




1064nm

V-Scan (HPK)




Normalized
by Cluster

HPK V-scan(532nm,Normalized)



532nm

HPK V-scan(1064,Normalized)



1064nm

位置分解能

CCD type	Scan方向	AC(um)	RLM(um)
EEV(3-phase)	H	3.0	1.4
EEV(3-phase)	V	2.2	2.6
HPK(2-phase)	H	2.1	1.8
HPK(2-phase)	V	1.8	2.1

本実験(レーザー)

$$\sigma_{EEV_H} = 1.4 \mu\text{m}$$

$$\sigma_{EEV_V} = 2.6 \mu\text{m}$$


$$\sigma_{HPK_H} = 1.8 \mu\text{m}$$

$$\sigma_{HPK_V} = 2.1 \mu\text{m}$$

1998 Beam test


$$\sigma_{EEV} = 2.94 \pm 0.23 \mu\text{m}$$

$$\sigma_{HPK} = 2.47 \pm 0.65 \mu\text{m}$$




Test setup of X-Y stage and Laser displacement meter


S7170








-13



27



20 μm (24.6x6 mm²)

300 μm

Fast Readout

Fast readout is preferable to reduce # of r.o. channel
($2000\text{cm}^2=3.2\times 10^8$ pixels, 6 ms r.o. \Rightarrow 53000 ch@1MHz)

Readout speed ~ few MHz - Limited by CCD

New CCD (HPK) ~10 MHz (20 MHz by sparse reset)

Present readout electronics: < 10 MHz

\Rightarrow New electronics needed

Study of S/N, spatial resolution, radiation hardness
with high speed readout